

GigaDevice Semiconductor Inc.

GD32F527R-START

Arm[®] Cortex[®]-M33 32-bit MCU

User Guide

Revision 1.1

(Jan. 2025)

Table of Contents

TABLE OF CONTENTS	1
LIST OF FIGURES	3
LIST OF TABLES	4
1. SUMMARY	5
2. FUNCTION PIN ASSIGNMENT	5
3. GETTING STARTED	5
4. HARDWARE LAYOUT OVERVIEW	7
4.1. Power supply	7
4.2. Boot option	7
4.3. LED	7
4.4. KEY	8
4.5. USART	8
4.6. USBFS	9
4.7. USBHS	10
4.8. Extension	10
4.9. GD-Link	11
4.10. MCU	12
4.11. Arduino	12
5. ROUTINE USE GUIDE	13
5.1. GPIO_Running_LED	13
5.1.1. DEMO purpose	13
5.1.2. DEMO running result	13
5.2. GPIO_Key_Polling_mode	13
5.2.1. DEMO purpose	13
5.2.2. DEMO running result	13
5.3. EXTI_Key_Interrupt_mode	14
5.3.1. DEMO purpose	14
5.3.2. DEMO running result	14
5.4. USART_HyperTerminal_Interrupt	14
5.4.1. DEMO purpose	14
5.4.2. DEMO running result	14
5.5. TIMER_Key_EXTI	15
5.5.1. DEMO purpose	15
5.5.2. DEMO running result	15
5.6. USB_MSC_Device	15
5.6.1. DEMO Purpose	15

5.6.2.	DEMO Running Result	16
5.7.	USB_MSC_Host	17
5.7.1.	DEMO purpose	17
5.7.2.	DEMO running result	17
6.	REVISION HISTORY	19

List of Figures

Figure 4-1 Schematic diagram of power supply.....	7
Figure 4-2 Schematic diagram of boot option	7
Figure 4-3 Schematic diagram of LED function	7
Figure 4-4 Schematic diagram of Key function	8
Figure 4-5 Schematic diagram of USART function	8
Figure 4-6 Schematic diagram of USBFS function	9
Figure 4-7 Schematic diagram of USBHS function	10
Figure 4-8 Schematic diagram of Extension Pin	10
Figure 4-9 Schematic diagram of GD-Link.....	11
Figure 4-10 Schematic diagram of MCU.....	12
Figure 4-11 Schematic diagram of Arduino	12

List of Tables

Table 2-1 Function pin assignment	5
Table 6-1 Revision history	19

1. Summary

GD32F527R-START uses GD32F527RST6 as the main controller. It uses GD-Link Mini USB interface to supply 5V power. SWD, Reset, Boot, User button key, LED, USART, USBFS, USBHS, Arduino, GD-Link and Extension Pins are also included. For more details please refer to GD32F527R-START-V1.0 schematic.

2. Function pin assignment

Table 2-1 Function pin assignment

Function	Pin	Description
LED	PA1	LED1
RESET		K1-Reset
KEY	PA0	K2-Wakeup
USART	PC10	USART2/3_TX
	PC11	USART2/3_RX
USB_FS	PA9	USBFS_VBUS
	PA11	USBFS_DM
	PA12	USBFS_DP
	PA10	USBFS_ID
USB_HS	PC3	USB_HS_ULPI_NXT
	PC2	USB_HS_ULPI_DIR
	PC0	USB_HS_ULPI_STP
	PA5	USB_HS_ULPI_CK
	PB5	USB_HS_ULPI_D7
	PB13	USB_HS_ULPI_D6
	PB12	USB_HS_ULPI_D5
	PB11	USB_HS_ULPI_D4
	PB10	USB_HS_ULPI_D3
	PB1	USB_HS_ULPI_D2
	PB0	USB_HS_ULPI_D1
	PA3	USB_HS_ULPI_D0


3. Getting started

The START board uses GD-Link Mini USB connector to get power DC +5V, which is the hardware system normal work voltage. A GD-Link on board is necessary in order to download and debug programs. Select the correct boot mode and then power on, the

LEDPWR will turn on, which indicates that the power supply is OK.


There are Keil version and IAR version of all projects. Keil version of the projects are created based on Keil MDK-ARM 5.28 uVision5. IAR version of the projects are created based on IAR Embedded Workbench for ARM 8.32.1. During use, the following points should be noted:

1. If you use Keil uVision5 to open the project, you need to install the latest version of GigaDevice.GigaDevice.GD32F5xx_DFP to load the related files.
2. If you use IAR to open the project, you need to install the latest version of IAR_GD32F5xx_ADDON to load the related files.




4.4. KEY

Figure 4-4 Schematic diagram of Key function




4.5. USART

Figure 4-5 Schematic diagram of USART function




4.6. USBFS

Figure 4-6 Schematic diagram of USBFS function




USBHS

Figure 4-7 Schematic diagram of USBHS function




Extension

Figure 4-8 Schematic diagram of Extension Pin




4.9. GD-Link

Figure 4-9 Schematic diagram of GD-Link




4.10. MCU

Figure 4-10 Schematic diagram of MCU



4.11. Arduino

Figure 4-11 Schematic diagram of Arduino



5. Routine use guide

5.1. GPIO_Running_LED

5.1.1. DEMO purpose

This demo includes the following functions of GD32 MCU:

- Learn to use GPIO control the LED.
- Learn to use SysTick to generate 1ms delay.

GD32F527R-START board has one LEDs. The LED1 is controlled by GPIO. This demo will show how to light the LEDs.

5.1.2. DEMO running result

Download the program <01_GPIO_Running_LED> to the START board, LED1 will flash every 1000ms, and repeat the process.

5.2. GPIO_Key_Polling_mode

5.2.1. DEMO purpose

This demo includes the following functions of GD32 MCU:

- Learn to use GPIO control the LED and the Key.
- Learn to use SysTick to generate 1ms delay.

GD32F527R-START board has two keys and one LEDs. The two keys are Reset key and Wakeup key. The LED1 is controlled by GPIO.

This demo will show how to use the Wakeup key to control the LED1. When press down the Wakeup Key, it will check the input value of the IO port. If the value is 1 and will wait for 100ms. Check the input value of the IO port again. If the value still is 1, it indicates that the button is pressed successfully and toggle LED1.

5.2.2. DEMO running result

Download the program <02_GPIO_Key_Polling_mode> to the START board, Press down the Wakeup Key, LED1 will be turned on. Press down the Wakeup Key again, LED1 will be turned off.

5.3. EXTI_Key_Interrupt_mode

5.3.1. DEMO purpose

This demo includes the following functions of GD32 MCU:

- Learn to use GPIO control the LED and the KEY.
- Learn to use EXTI to generate external interrupt.

GD32F527R-START board has two keys and one LED. The two keys are Reset key, and Wakeup key. The LED1 is controlled by GPIO.

This demo will show how to use the EXTI interrupt line to control the LED1. When press down the Wakeup Key, it will produce an interrupt. In the interrupt service function, the demo will toggle LED1.

5.3.2. DEMO running result

Download the program <03_EXTI_Key_Interrupt_mode> to the START board, LED1 is turned on and off for test. Press down the Wakeup Key, LED1 will be turned on. Press down the Wakeup Key again, LED1 will be turned off.

5.4. USART_HyperTerminal_Interrupt

5.4.1. DEMO purpose

This demo includes the following functions of GD32 MCU:

- Learn to use the USART transmit and receive interrupts to communicate with the serial terminal tool.

5.4.2. DEMO running result

Download the program < 04_USART_HyperTerminal_Interrupt > to the START board, connect serial cable to USART. Firstly, all the LEDs flash 2 times for test. Then, the USART sends the tx_buffer array (from 0x00 to 0xFF) to the serial terminal tool supporting hex format communication and waits for receiving data of BUFFER_SIZE bytes from the serial terminal. The data MCU has received is stored in the rx_buffer array. After that, compare tx_buffer with rx_buffer. If tx_buffer is same with rx_buffer, LED1, LED2, LED3, LED4 flash by turns. Otherwise, LED1, LED2, LED3 and LED4 turn on.

The output information via the serial port is as following.

```

00 01 02 03 04 05 06 07 08 09 0A 0B 0C 0D 0E 0F 10 11 12 13 14 15 16 17 18 19 1A 1B
1C 1D 1E 1F 20 21 22 23 24 25 26 27 28 29 2A 2B 2C 2D 2E 2F 30 31 32 33 34 35 36 37
38 39 3A 3B 3C 3D 3E 3F 40 41 42 43 44 45 46 47 48 49 4A 4B 4C 4D 4E 4F 50 51 52 53
54 55 56 57 58 59 5A 5B 5C 5D 5E 5F 60 61 62 63 64 65 66 67 68 69 6A 6B 6C 6D 6E 6F
70 71 72 73 74 75 76 77 78 79 7A 7B 7C 7D 7E 7F 80 81 82 83 84 85 86 87 88 89 8A 8B
8C 8D 8E 8F 90 91 92 93 94 95 96 97 98 99 9A 9B 9C 9D 9E 9F A0 A1 A2 A3 A4 A5 A6 A7
A8 A9 AA AB AC AD AE AF B0 B1 B2 B3 B4 B5 B6 B7 B8 B9 BA BB BC BD BE BF C0 C1 C2 C3
C4 C5 C6 C7 C8 C9 CA CB CC CD CE CF D0 D1 D2 D3 D4 D5 D6 D7 D8 D9 DA DB DC DD DE DF
EO E1 E2 E3 E4 E5 E6 E7 E8 E9 EA EB EC ED EE EF FO F1 F2 F3 F4 F5 F6 F7 F8 F9 FA FB
FC FD FE FF

```

5.5. TIMER_Key_EXTI

5.5.1. DEMO purpose

This demo includes the following functions of GD32 MCU:

- Learn to use EXTI to generate external interrupt
- Learn to use TIMER to generate PWM

This demo will show how to use the TIMER PWM to trigger EXTI interrupt to toggle the state of LED1 and EXTI interrupt line to control the LED1. When press down the Wakeup key, it will produce an interrupt. In the interrupt service function, the demo will toggle LED1.

5.5.2. DEMO running result

Download the program <05_TIMER_Key_EXTI> to the START board, the LED1 is flashed once for test, press down the Wakeup key, LED1 will be turned on. Press down the Wakeup key again, LED1 will be turned off. Connect PA6 (TIMER2_CH0) and PA1(LED1) with DuPont line. The LED1 will be toggled every 500ms.

5.6. USB_MSC_Device

5.6.1. DEMO Purpose

This demo includes the following functions of GD32 MCU:


- Learn how to use the USBFS/USBHS peripheral mode
- Learn how to implement USB MSC (mass storage) device

This demo mainly implements a U disk. U disk is currently very widely used removable MSC devices. MSC, the Mass Storage Device Class, is a transport protocol between a computer and mobile devices, which allow a universal serial bus (USB) equipment to access a host computing device, file transfer between them, mainly including mobile hard disk, mobile U disk drive, etc... The MSC device must have a storage medium, and this Demo uses the MCU's internal SRAM as the storage medium. For more details of the MSC protocol please refer to the MSC protocol standard.

MSC device will use a variety of transport protocols and command formats for communication, so it need to choose the appropriate protocol and command format in the realization of the application. This Demo selects the BOT (bulk only transport) protocol and the required SCSI (small computer interface) command, and is compatible with a wide variety of Window operating systems. Specific BOT protocol and SCSI command specification please refer to the standard of their agreement.

5.6.2. DEMO Running Result

After doing this, download the program <06_USB_MSC_Device> to the START board and run. When the START board connect to the PC, you will find a USB large capacity storage device is in the universal serial bus controller, and there is 1 more disk drives in the equipment manager of PC, as shown below:



Then, after opening the resource manager, you will see more of the 1 disk, as shown in the following diagram:



At this point, the write/read/formatting operation can be performed as the other mobile devices.

5.7. USB_MSC_Host

5.7.1. DEMO purpose

This demo includes the following functions of GD32 MCU:

- Learn to use the USBFS/USBHS as a MSC host
- Learn the operation between the MSC host and the Udisk

GD32F527R-START board integrates USBFS module and the USBHS module, and the modules can be used as USB device, USB host or OTG device. This demo mainly shows how to use the USBFS and USBHS as a USB MSC host to communicate with external Udisk.

5.7.2. DEMO running result

Insert the OTG cable to USB port. Then, download the program <07_USB_MSC_Host> to the START board and run.

If an Udisk has been attached, the user will see the information of Udisk enumeration on the serial assistant. Pressing the Wakeup key, the user will see the root content of the Udisk, then the MSC Host write file to the Udisk, and the user will see information that the MSC host demo is end.

```
++++USB host library started++++

> Reset the USB device.
> Full speed device detected.

> Device Attached.
VID: 30DEh
PID: 6544h
> Mass storage device connected.
Manufacturer: KIOXIA
Product: TransMemory
Serial Number: 0022CFF6BD8EC761D322083E

> Enumeration completed.
_____

> To see the disk information and write file to the Udisk:
> Press Wakeup Key...

> File System initialized.
> Disk capacity: 31001148928 Bytes.
> Exploring disk flash ...
    |__System Volume Information
    |__GD32.TXT
    |__LED.BIN
    |__TEST.TXT

> Writing File to disk flash ...
> GD32.TXT be opened for write.
> File content compare: SUCCESS.
> The MSC host demo is end.
```

6. Revision history

Table 6-1 Revision history

Revision No.	Description	Date
1.0	Initial Release	Mar.18, 2024
1.1	Update chapter 3	Jan.25, 2025

Important Notice

This document is the property of GigaDevice Semiconductor Inc. and its subsidiaries (the "Company"). This document, including any product of the Company described in this document (the "Product"), is owned by the Company under the intellectual property laws and treaties of the People's Republic of China and other jurisdictions worldwide. The Company reserves all rights under such laws and treaties and does not grant any license under its patents, copyrights, trademarks, or other intellectual property rights. The names and brands of third party referred thereto (if any) are the property of their respective owner and referred to for identification purposes only.

The Company makes no warranty of any kind, express or implied, with regard to this document or any Product, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose. The Company does not assume any liability arising out of the application or use of any Product described in this document. Any information provided in this document is provided only for reference purposes. It is the responsibility of the user of this document to properly design, program, and test the functionality and safety of any application made of this information and any resulting product. Except for customized products which has been expressly identified in the applicable agreement, the Products are designed, developed, and/or manufactured for ordinary business, industrial, personal, and/or household applications only. The Products are not designed, intended, or authorized for use as components in systems designed or intended for the operation of weapons, weapons systems, nuclear installations, atomic energy control instruments, combustion control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, life-support devices or systems, other medical devices or systems (including resuscitation equipment and surgical implants), pollution control or hazardous substances management, or other uses where the failure of the device or Product could cause personal injury, death, property or environmental damage ("Unintended Uses"). Customers shall take any and all actions to ensure using and selling the Products in accordance with the applicable laws and regulations. The Company is not liable, in whole or in part, and customers shall and hereby do release the Company as well as its suppliers and/or distributors from any claim, damage, or other liability arising from or related to all Unintended Uses of the Products. Customers shall indemnify and hold the Company as well as its suppliers and/or distributors harmless from and against all claims, costs, damages, and other liabilities, including claims for personal injury or death, arising from or related to any Unintended Uses of the Products.

Information in this document is provided solely in connection with the Products. The Company reserves the right to make changes, corrections, modifications or improvements to this document and Products and services described herein at any time, without notice.